

PRODUCT-DETAILS

3558N-C86511 B

Mechanical Controls 1 gang(s), Single push button 1 pole, 1NC 1CO white - Variant+



General Information	
Extended Product Type	3558N-C86511 B
Product ID	2CHN588652C4500
EAN	8592624021414
Catalog Description	Mechanical Controls 1 gang(s), Single push button 1 pole, 1NC 1CO white - Variant+
Long Description	Rocker push-switch 1gang 2way with N terminal, with transparent lens
Installation	
Instructions and	No document needed
Manuals	
Mounting Type	Surface Mounted
Type of Fastening	Screw
Environmental	
Degree of Protection	IP54

© 2024 ABB. All rights reserved.

Subject to change without notice

Technical	
Data Sheet, Technical Information	No document needed
Contacts Configuration	1 NO, 1 NC
Number of Poles	1
Number of Gangs	1
Number of Rocker Switches	1
Action Type of the Contact Element (acc. to IEC 60947-5-1)	Basic element with complete housing
Actuator Type	Rocker
Connection Type	Screw
Battery Weight	0 g
Number of Batteries	0

Electrical	
Rated Voltage (U _r)	250 V
Rated Current (In)	10 A
Number of Contacts CO	1
Number of Contacts NC	1

Design	
Design Range	Variant+
Surface Finishing	Untreated Glossy
Material	Plastic Thermoplastic
Label Space Provided	No
Color	white

Dimensions	
Product Net Weight	123 g
Built-In Depth (t ₂)	0 mm

Ordering	
Replaced Product ID	3558N-C86511 B
(OLD)	

Material Compliance	
RoHS Information	2CHC663076X0201
RoHS Status	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019
REACH Declaration	2CHC663076X0201
REACH Information	False - does not contain substances > 0.1 mass percentage
REACH Date	20221103
Conflict Minerals	9AKK108468A3363
Reporting Template	

© 2024 ABB. All rights reserved.

Subject to change without notice

Certificates and Declarations

Declaration of Conformity - CE No declaration needed

Classifications	
ETIM 9	EC000029 - Push button
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)
WEEE B2C / B2B	Business To Consumer

Categories

 ${\sf Low \ Voltage \ Products \ and \ Systems \rightarrow Wiring \ Accessories - \ Light \ Switch \ Ranges \rightarrow \ Surface \ Mounted \ Range \rightarrow \ Mechanical \ Controls \ Surface \ Mounted \ Range \ Surface \ Mounted \ Range \ Surface \ Surface \ Mounted \ Range \ Surface \ Surface$



3/3